

Configuration table for lighting fixtures with emergency features

Model	Lamp power	Emergency lighting time	Battery type	Enclosure type
HRY97-20□J	20W	90min	Ni-CD	Type II
HRY97-40□J	40W	90min	Ni-CD	Type II
HRY97-60□J	60W	90min	Ni-CD	Type III
HRY97-20□J	20W	180min	Ni-CD	Type III
HRY97-40□J	40W	180min	Ni-CD	Type III
HRY97-60□J	60W	180min	Ni-CD	Type III
HRY97-20□J	20W	90min	Ni-MH	Type II
HRY97-40□J	40W	90min	Ni-MH	Type II
HRY97-60□J	60W	90min	Ni-MH	Type III
HRY97-20□J	20W	180min	Ni-MH	Type II
HRY97-40□J	40W	180min	Ni-MH	Type II
HRY97-60□J	60W	180min	Ni-MH	Type III

Selection table

Type / Ordering code	Lamp power(W)	Weight (kg)	Type / Ordering code	Lamp power(W)	Weight (kg)	Type / Ordering code	Lamp power(W)	Weight (kg)
HRY97-20X	20	2.90	HRY97-40X	40	4.70	HRY97-60X	60	5.50
HRY97-20G	20	3.90	HRY97-40G	40	5.70	HRY97-60G	60	6.50
HRY97-20B	20	3.30	HRY97-40B	40	5.10	HRY97-60B	60	5.90
HRY97-20W	20	3.00	HRY97-40W	40	4.80	HRY97-60W	60	5.60
HRY97-20H	20	3.00	HRY97-40H	40	4.80	HRY97-60H	60	5.60
HRY97-20F	20	3.00	HRY97-40F	40	4.80	HRY97-60F	60	5.60
HRY97-20QT	20	3.40	HRY97-40QT	40	5.20	HRY97-60QT	60	6.00
HRY97-20XJ	20	5.70	HRY97-40XJ	40	5.90	HRY97-60XJ	60	6.70
HRY97-20GJ	20	6.70	HRY97-40GJ	40	6.90	HRY97-60GJ	60	7.70
HRY97-20BJ	20	6.10	HRY97-40BJ	40	6.30	HRY97-60BJ	60	7.10
HRY97-20WJ	20	5.80	HRY97-40WJ	40	6.10	HRY97-60WJ	60	6.80
HRY97-20HJ	20	5.80	HRY97-40HJ	40	6.10	HRY97-60HJ	60	6.80
HRY97-20FJ	20	5.80	HRY97-40FJ	40	6.10	HRY97-60FJ	60	6.80
HRY97-20QTJ	20	4.60	HRY97-40QTJ	40	6.40	HRY97-60QTJ	60	7.20

Note: 1. Products above include all the mounting accessories listed in Mounting Accessories & Spare Parts Table (see P2/39).